

PRODUCT DATA

4/6-ch. Input Module LAN-XI 51.2 kHz Type 3050

The core of the LAN-XI range of input modules, these modules are designed to cover as many sound and vibration measurement applications as possible.

Type 3050 comes in two basic variants, offering the choice between four and six high-precision input channels with an input range from DC to 51.2 kHz Type 3050 works equally well as a single-module system, or as part of a large LAN-XI measurement system – making it one of the most flexible data acquisitions modules on the market. In addition, interchangeable front panels give you the flexibility to use a wide range of transducers.



Uses and Features

Uses

- General sound and vibration measurements
- Measurement front-end module for PULSE™ measurement and analysis software
- Front-end for PC-based Data Recorder Type 7708
- Single-module measurements
- Multi-module measurements/ distributed system
- Stand-alone recording (no PC) using LAN-XI Notar™ software

Features

- 4 or 6 input channels
- DC to 51.2 kHz input range
- 131 ksample/s sampling rate
- Power for 200 V microphones
- Dyn-X technology
- REq-X technology
- Supports TEDS transducers
- Interchangeable front panels

One Cable Operation

You can use standard LAN cables for synchronous sampling between modules and system power, thanks to Power over Ethernet (PoE). This minimises the number of cables required and results in lower cost, less downtime, easier maintenance, and greater flexibility of installation.

Power over Ethernet

PoE is implemented according to IEEE 802.3af. PoE is wired Ethernet LAN technology that, with a suitable PoE LAN switch, allows the power needed for each module to be carried by screened shielded twisted pair (S/STP or S/FTP) CAT6 LAN cables rather than by separate power cables. This minimises the number of cables required and results in lower cost, less downtime, easier maintenance and greater installation flexibility. PoE switches, such as 10-port Gigabit Managed Switch with PTP and PoE (8 ports) UL-0265, and PoE Injectors, such as ZyxEL® PoE-12 Power over Ethernet (a single-port PoE injector), can be used.

Built for Field and Lab Use

The modules and the detachable front plates are cast in magnesium for maximum stability, light weight, and tough field use.

Interchangeable Front Panels

The modules allow front panels to be interchanged freely, with a variety of connectors for different transducers and applications. This results in fewer patch panels, less cable “spaghetti”, fewer cable adaptors and faster system setup.

Independent Channels

The input channels on a module can be set up independently. You can set up the high-pass filters and input gain separately and attach different types of transducer to different channels.

IEEE 1451.4 Transducers

All input modules support TEDS transducers. This allows automatic front-end and analyzer setup based on TEDS information stored in the transducer, for example, sensitivity, serial number, manufacturer and calibration date. The individual frequency response of a transducer can be corrected for using PULSE’s Transducer Response Equalisation, REq-X, to achieve higher accuracy over extended frequency ranges.

Overload

Constant Current Line Drive (CCLD) conditioning monitors the supply voltage used by CCLD-compatible transducers. Available CCLD transducers include:

- Accelerometers
- Charge amplifiers
- Microphone preamplifiers
- Tacho probes

If conditioning errors, such as a broken cable, are detected, an error is indicated as an overload on the specific channel connector (using a ring-LED around the connector) and in the PC software.





Overload indications for input channels include (see Specifications for details):

- Signal overload with adjustable detection level
- CCLD overload: detection of cable break, short-circuit or CCLD transducer working point fault
- Microphone preamplifier overload: detection of microphone preamplifier current consumption too high or too low
- Common mode voltage overload – relevant when input coupling is floating

Ground-loop Noise Suppression

The module’s floating/grounded, differential input design and the fact that all external connections (LAN, power supply) are galvanically isolated in the module provide optimal ground-loop noise suppression.

Compliance with Standards

   	<p>CE-mark indicates compliance with: EMC Directive and Low Voltage Directive</p> <p>RCM mark indicates compliance with applicable ACMA technical standards – that is, for telecommunications, radio communications, EMC and EME</p> <p>China RoHS mark indicates compliance with administrative measures on the control of pollution caused by electronic information products according to the Ministry of Information Industries of the People's Republic of China</p> <p>WEEE mark indicates compliance with the EU WEEE Directive</p>
Safety	EN/IEC 61010–1 and ANSI/UL 61010–1: Safety requirements for electrical equipment for measurement, control and laboratory use
EMC Emission	EN/IEC 61000–6–3: Generic emission standard for residential, commercial, and light-industrial environments CISPR 22: Radio disturbance characteristics of information technology equipment. Class B Limits
EMC Immunity	EN/IEC 61000–6–1: Generic standards – Immunity for residential, commercial and light industrial environments EN/IEC 61000–6–2: Generic standards – Immunity for industrial environments EN/IEC 61326: Electrical equipment for measurement, control and laboratory use – EMC requirements Note: The above is only guaranteed using accessories listed in this Product Data
Temperature	IEC 60068–2–1 & IEC 60068–2–2: Environmental Testing. Cold and Dry Heat Ambient Operating Temperature: –10 to +55°C (14 to 131°F) Storage Temperature: –25 to +70°C (–13 to +158°F)
Humidity	IEC 60068–2–78: Damp Heat: 93% RH (non-condensing at 40°C (104°F))
Mechanical (non-operating)	IEC 60068–2–6: Vibration: 0.3 mm, 2 g, 10 – 500 Hz IEC 60068–2–27: Shock: 100 g IEC 60068–2–29: Bump: 1000 bumps at 25 g
Enclosure	IEC 60529: Protection provided by enclosures: IP 31

EFFECT OF RADIATED AND CONDUCTED RF, MAGNETIC FIELD AND VIBRATION

Radiated RF: 80–2700 MHz, 80% AM 1 kHz, 10 V/m

Conducted RF: 0.15–80 MHz, 80% AM 1 kHz, 10 V

Magnetic Field: 30 A/m, 50 Hz

Vibration: 5–500 Hz, 12.7 mm, 15 m/s²

Input measured with shorted input. All values are RMS. Conducted RF immunity on all channels is only guaranteed using an external connection from measuring ground to chassis terminal

Input	Radiated RF	Conducted RF	Magnetic Field	Vibration
Direct/CCLD	<250 μ V	<300 μ V	<4 μ V	<80 μ V
Preamplifier	<250 μ V	<50 μ V	<8 μ V	<80 μ V

Specifications – LAN Interface

CONNECTOR

RJ 45 (10baseT/100baseTX) connector complying with IEEE-802.3 100baseX

Types 3660-C and -D permit the use of a ruggedized RJ45 data connector (Neutrik NE8MC-1) to screw the cable to the frame

Types 3660-C and -D communicate at 1000 Mbits/s – shielded cables of type “CAT 5e” or better should be used

Individual modules communicate at 100 Mbits/s

All LAN connectors support MDIX, which means that cables may be “crossed” or not

For stand-alone modules, PoE is also supported (IEEE 802.3af). PoE requires screened shielded twisted pair (S/STP or S/FTP) CAT6 LAN cables

PROTOCOL

The following standard protocols are used:

- TCP
- DHCP (incl. Auto-IP)
- DNS (on top of UDP)
- IEEE 1588–2002 (on top of UDP)
- IP
- Ethernet

ACQUISITION PERFORMANCE

Each LAN-XI module generates data at almost 20 Mbit/s when measuring six channels at 51.2 kHz bandwidth. The modules are capable

of handling their own maximum traffic while the built-in switch in the frame's backplane has more than sufficient capacity. This means that bottlenecks can only occur outside these, for example in:

- External switches
- PC

For convenience, it is possible to daisy-chain LAN-XI frames. However, it is not recommended to daisy-chain more than two frames. For larger configurations, a star configuration with a central switch is recommended. This must have a switch capacity well beyond $N \times 20$ Mbit/s, where N is the total number of modules

PTP PERFORMANCE

PTP Synchronisation (with 1 Gigabit LAN Switch):

Typical sample synchronisation better than 200 ns

(approx. $\pm 0.07^\circ$ @ 1 kHz, $\pm 2^\circ$ @ 25.6 kHz)

Tested with:

- Cisco[®] SG300-10MP, 10-port 10/100/1000 Managed Gigabit Switch with Maximum PoE (8 ports)
- Netgear[®] 5-port Gigabit Switch GS105

Better performance can be expected with a dedicated PTP switch:

- UL-0265: 10-port Gigabit Managed Switch with PTPv2 and PoE (8 ports).

This is a dedicated PTP switch, preconfigured for optimal use with LAN-XI

Specifications – 4/6-ch. Input Module LAN-XI 51.2 kHz Type 3050

POWER REQUIREMENTS

DC Input: 10–32 V DC

Connector: LEMO coax., FFA.00.113, ground on shield

Power Consumption:

DC Input: <15 W

Supply via PoE: According to IEEE 802.3af, Max. cable length 50 m

Temperature Protection:

Temperature sensor limits module's internal temperature to 80°C (176°F).

If temperature exceeds limit, system will automatically enable fan in

LAN-XI frame or shut down module outside frame

DIMENSIONS AND WEIGHT

Height: 132.6 mm (5.22")

Width: 27.5 mm (1.08")

Depth: 250 mm (9.84")

Weight: 750 g (1.65 lb)

Frequency Range	DC to 51.2 kHz Lower frequency range can be set in PULSE software					
Sampling Rate	131 ksamples/s					
A/D Conversion	2 × 24 bit					
Data Transfer	24 bit					
Input Voltage Range	10 V _{peak} Extended range: 31.6 V _{peak}					
Input Signal Coupling	Differential	Signal ground is "floating" (1 MΩ re chassis)				
	Single-Ended	Signal ground is connected to chassis ("Grounded")				
Input Impedance	Direct, Microphone: 1 MΩ <300 pF					
	CCLD: >100 kΩ <300 pF					
Absolute Maximum Input	±60 V _{peak} without damage					
High-pass Filters		–0.1 dB *	–10% @ **	–3 dB @ **	Slope	
* Defined as the lower frequency, f _L , for guaranteed fulfillment of –0.1 dB accuracy in 10 V _{peak} range	0.1 Hz –10% analog high-pass filter	0.5 Hz	0.1 Hz	0.05 Hz	–20 dB/dec.	
	0.7 Hz –0.1 dB digital high-pass filter	0.7 Hz	0.15 Hz	0.073 Hz		
** Defined as the nominal –10%/3 dB filter frequency	1 Hz –10% digital high-pass filter	5 Hz	1.0 Hz	0.5 Hz	–20 dB/dec.	
	7 Hz –0.1 dB digital high-pass filter	7 Hz	1.45 Hz	0.707 Hz		
	22.4 Hz –0.1 dB analog high-pass filter	22.4 Hz	15.8 Hz	12.5 Hz	–60 dB/dec.	
	Intensity filter (analog)	115 Hz	23.00 Hz	11.5 Hz	–20 dB/dec.	
Absolute Amplitude Precision, 1 kHz, 1 V_{input}	±0.05 dB, typ. ±0.01 dB					
Amplitude Linearity (linearity in one range)	0 to 80 dB below full scale	±0.05 dB, typ. ±0.01 dB				
	80 to 100 dB below full scale	±0.2 dB, typ. ±0.02 dB				
	100 to 120 dB below full scale	typ. ±0.02 dB				
	120 to 140 dB below full scale	typ. ±0.02 dB				
	140 to 160 dB below full scale	typ. ±1 dB				
Overall Frequency Response re 1 kHz, from lower limit f _L to upper limit f _U f _L is defined as the lower frequency for guaranteed fulfillment of –0.1 dB accuracy in 10 V _{peak} range (see under High-pass Filters) f _U is defined as the chosen frequency span. DC (f _L = 0)	±0.1 dB ±0.3 dB in 31.6 V range					
Noise * Measured lin. 10 Hz to 25.6 kHz or lin. 10 Hz to 51.2 kHz: (Input terminated by 50 Ω or less)	Signal level <316 mV_{peak} 10 Hz to 25.6 kHz 10 Hz to 51.2 kHz	10 V _{peak}	Guaranteed		Typical	
			Lin*	1 kHz	Lin*	1 kHz
	Signal level >316 mV_{peak} 10 Hz to 25.6 kHz 10 Hz to 51.2 kHz	10 V _{peak}	<4 μV _{rms} <13 μV _{rms}	<25 nV _{rms} /√Hz	<3 μV _{rms} <10 μV _{rms}	<19 nV _{rms} /√Hz
	Signal level <1 V_{peak} 10 Hz to 25.6 kHz 10 Hz to 51.2 kHz	31.6 V _{peak}	<60 μV _{rms} <350 μV _{rms}	<375 nV _{rms} /√Hz	<50 μV _{rms} <250 μV _{rms}	<313 nV _{rms} /√Hz
Signal level >1 V_{peak} 10 Hz to 25.6 kHz 10 Hz to 51.2 kHz	31.6 V _{peak}	<20 μV _{rms} <45 μV _{rms}	<125 nV _{rms} /√Hz	<15 μV _{rms} <35 μV _{rms}	<95 nV _{rms} /√Hz	
Spurious-free Dynamic Range re Full-scale Input (Input terminated by 50 Ω or less) Spurious-free Dynamic Range is defined as the ratio of the rms full-scale amplitude to the rms value of the largest spurious spectral component (non-harmonic)	Input Range	Typical				
		10 V _{peak}	160 dB			
	31.6 V _{peak}	140 dB				
DC Offset re Full Scale Measured after automatic DC compensation at current temperature when changing from AC to DC coupling or changing input range when DC coupled	Guaranteed		Typical			
	<–90 dB		–100 dB			

Harmonic Distortion (all harmonics)		Guaranteed	Typical
		-80 dB (-60 dB in 31.6 V range)	-100 dB @ 1 kHz (-80 dB @ 1 kHz in 31.6 V range)
Crosstalk: Between any two channels of a module or between any two channels in different modules		Frequency Range	Guaranteed Typical
		0-51.2 kHz	-100 dB -140 dB
Channel-to-Channel Match		Guaranteed	Typical
(10 V_{peak} input range)	Maximum Gain Difference f_L is defined as the -0.1 dB frequency of the high-pass filter	0.2 dB from lower frequency limit, f_L , to 51.2 kHz (0.4 dB at -10% filter frequency)	±0.05 dB
	Maximum Phase Difference (within one frame) f_L is defined as the -0.1 dB frequency of the high-pass filter	<p>Max. phase diff. (degrees)</p> <p>DC</p> <p>f_L 10f_L 6.4k 51.2k Hz</p> <p>080229</p>	
Additional PTP sync. error (phase difference) between modules/frames (using a single standard gigabit switch)		Typical: <200 ns (approx. ±0.07° @ 1 kHz, ±2° @ 25.6 kHz)	
Channel-to-Channel Match (31.6 V_{peak} input range)		Maximum Gain Difference	0.6 dB from lower frequency limit, f_L , to 51.2 kHz (1 dB at -10% filter frequency)
		Maximum Phase Difference (within one frame)	4° from lower frequency limit, f_L , to 51.2 kHz
Sound Intensity Phase Match (only for using intensity filter and in 10 V_{peak} input range)	Frequency Range	Guaranteed Phase Match	Typical Phase Match
	50-250 Hz	±0.017°	±0.005°
	250 Hz-2.5 kHz	0.017° × (f/250)	±0.005°
All channels matched	2.5-6.4 kHz	±0.17°	±0.08°
Common Mode Rejection in 10 V_{peak} input range		Guaranteed	Typical
Values for 31.6 V _{peak} range are 10 dB lower.		0-120 Hz	70 dB
		120 Hz-1 kHz	55 dB
		1-51.2 kHz	30 dB
Absolute Max. Common Mode Voltage		±5 V _{peak} without damage	
		±4 V _{peak} without clipping	
		If common mode voltage exceeds the max. value, care must be taken to limit the signal ground current in order to prevent damage. Max. is 100 mA. The instrument will limit the voltage to the stated max. "without damage" common mode value	
Anti-aliasing Filter At least 90 dB attenuation of those frequencies which can cause aliasing	Filter Type	3rd order Butterworth	
	-0.1 dB @	51.2 kHz	
	-3 dB @	128 kHz	
	Slope	-18 dB/octave	
Supply for Microphone Preamplifiers		±14.0 V, max. 100 mA per channel (max. 100 mA total/module)	
Supply for Microphone Polarization		200 V ±1 V, or 0 V (set per channel)	
Supply for CCLD		4 to 5 mA from 24 V source, option to DC-couple CCLD power supply	
Tacho Supply		CCLD for Type 2981 (Power supply for legacy types MM-0012 and MM-0024 not available)	
Analog Special Functions	Microphone Charge Injection Calibration: All modules with 7-pin LEMO support CIC via dedicated application software and OLE interface Transducers: Supports IEEE 1451.4-capable transducers with standardised TEDS (up to 100 m (328 ft) cable length)		
Overload Detection	Signal Overload: Adjustable detection level ±1 V _{peak} to ±10 V _{peak} . Default level ±10 V _{peak} (CCLD mode ±7 V _{peak}) (31.6 V range: ±31.6 V) can be set in PULSE Transducer Database CCLD Overload: Detection of cable break or short-circuit + detection of CCLD transducer working point fault. Detection level: +2 V/20 V Microphone Preamplifier Overload: Detection of microphone preamplifier current consumption too high or too low. Detection level default 10 mA/1 mA Adjustable detection level 1 to 20 mA or 100 mA if disabled Common Mode Voltage Overload: Detection level: ±3.0 V		
Protection	If signal input level exceeds the measuring range significantly, the input will go into protection mode until the signal goes below the detection level again for at least 0.5 s. While in protection mode, the input is partly switched off and the input impedance is greatly increased. (The measured value will be strongly attenuated but still detectable) In DC mode -10 V _{peak} range, the detection limit is ±12 V. In all other measuring modes (except CCLD) the limit is ±50 V _{peak} including DC component or ±12 V _{peak} AC (In CCLD mode the limit is +50/-2 V _{peak} including DC component or ±12 V _{peak} AC) In the 31.6 V range, the limit is ±50 V _{peak}		

Ordering Information

Type 3050-A-060 6-ch. Input Module LAN-XI 51.2 kHz (Mic, CCLD, V)

includes the following accessories:

- UA-2100-060: LAN-XI Detachable front panel with 6 BNC input connectors
- ZG-0426: Mains Adaptor (100 – 240 V)
- AO-1450: Shielded CAT 6 LAN Cable with RJ 45 (2 m)

Type 3050-A-040 4-ch. Input Module LAN-XI 51.2 kHz (Mic, CCLD, V)

includes the following accessories:

- UA-2100-040: LAN-XI Detachable front panel with 4 BNC input connectors
- ZG-0426: Mains Adaptor (100 – 240 V)
- AO-1450: Shielded CAT 6 LAN Cable with RJ 45 (2 m)

OPTIONAL ACCESSORIES

AO-0090	7-pin LEMO to BNC male (1.2 m) for floating ground
AO-0091	7-pin LEMO to BNC female (1.2 m) for floating ground
AO-0526	4-pin Microtech to 3 × BNC Cable
AO-0546	DC Power Cable, Car Utility Socket to 1 module
AO-0548	DC Power Cable, Source to 4 modules
JJ-0081	BNC Adaptor, female to female

JJ-0152	BNC T-connector
JP-0145	BNC to 10–32 UNF Plug Adaptor
UA-1713	10 × 2 mm Hex Wrench (QX-1315) for front panel exchange
UL-0265	10-port Gigabit Managed Switch with PTP and PoE (8 ports)
WB-1497	20 dB Attenuator

SOFTWARE

Please refer to the System Data for PULSE Software ([BU 0229](#))

Service Products

3050-CAI	Type 3050 Initial Accredited Calibration
3050-CAF	Type 3050 Accredited Calibration
3050-CTF	Type 3050 Traceable Calibration
3050-TCF	Type 3050 LAN-XI Conformance Test with Certificate

A wide range of Brüel & Kjær Accelerometers, Microphones, Preamplifiers and Sound Intensity Probes is available for use with a LAN-XI system. The system supports IEEE 1451.4-capable transducers with standardised TEDS

BP 2330-13 2013-09



TRADEMARKS

ICP is a registered trademark of PCB Group Inc. · Netgear is a registered trademark of NetGear, Inc. · Cisco is a registered trademark of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries · ZYXEL is a registered trademarks of ZYXEL Communications Corp

Brüel & Kjær reserves the right to change specifications and accessories without notice. © Brüel & Kjær. All rights reserved.

HEADQUARTERS: Brüel & Kjær Sound & Vibration Measurement A/S · DK-2850 Nærum · Denmark
Telephone: +45 7741 2000 · Fax: +45 4580 1405 · www.bksv.com · info@bksv.com

Local representatives and service organisations worldwide

